

EPE-ED3 Series LED Emergency Inverter

-This LED emergency inverter with battery backup unit provides.

120 Minutes duration during main power failure.

Wide range input voltage with high output voltage.

Suitable for LED tube, bulb, MR16.

LiFePO4 battery optional.

CE and RoHS compliance.



RoHS CE



Parameter

Model	Input Voltage	Output Power	Charge Time	Discharge Duration	Battery	Test Mode
EPE-ED3-10W-MT-CD	85-265VAC	20W Max	24H	2H	Ni-Cd 12V 2000mAh	Manual Test
EPE-ED3-20W-MT-CD	85-265VAC	20W Max	24H	2H	Ni-Cd 12V 2000mAhx2	Manual Test
EPE-ED3-10W-MT-LI	85-265VAC	20W Max	24H	2H	LiFePO4 16V 1500mAh	Manual Test
EPE-ED3-20W-MT-LI	85-265VAC	20W Max	24H	2H	LiFePO4 16V 1500mAhx2	Manual Test